

Decoy states for quantum key distribution based on decoherence-free subspaces

Zhen-Qiang Yin, Yi-Bo Zhao, Zheng-Wei Zhou*, Zheng-Fu Han*, Guang-Can Guo

Key Laboratory of Quantum Information
University of Science and Technology of China
Hefei 230026
China

Quantum key distribution with decoherence-free subspaces has been proposed to overcome the collective noise to the polarization modes of photons flying in quantum channel. Prototype of this scheme have also been achieved with parametric-down conversion source. However, a novel type of photon-number-splitting attack we proposed in this paper will make the practical implementations of this scheme insecure since the parametric-down conversion source may emit multi-photon pairs occasionally. We propose decoy states method to make these implementations immune to this attack. And with this decoy states method, both the security distance and key bit rate will be increased.

PACS numbers: 03.67.Dd

I. INTRODUCTION

As a combination of quantum mechanics and conventional cryptography, Quantum Key Distribution (QKD) [1, 2, 3], can help two distant peers (Alice and Bob) share secret string of bits, called key. Unlike conventional cryptography whose security is based on computation complexity, the security of QKD relies on the fundamental laws of quantum mechanics. Any eavesdropping attempt to an ideal QKD process will introduce an abnormal high bit error rate of the key. By comparing subset of the key, Alice and Bob can catch any eavesdropping attempt. Polarization and phase time of photons are the most common coding method to implement QKD. But, birefringence in optical fiber may depolarize the photons, which makes the polarization coding unsuitable for QKD based on fiber. Phase time coding is commonly used for fiber QKD. Using "Plug&Play" [3] or Faraday-Michelson interferometers[11], phase time coding can be free from polarization fluctuations due to birefringence of optical fiber. However, "Plug&Play" may be vulnerable for Trojan attack. And for Faraday-Michelson interferometers [11], it's very sensitive to phase fluctuations from arms between Alice's and Bob's interferometers. To overcome this problem, active compensation which makes the system more complicated and inefficient is used.

Alternatively, Walton *et al.* [4] proposed a novel QKD protocol based on decoherence-free space (DFS) and Boileau *et al.* [5] developed this scheme to use time-bin and polarization for encoding. In Boileau's scheme, Alice can encode her qubit in the two-photon states as follows: $|H\rangle|V\rangle$, $|V\rangle|H\rangle$, $(|H\rangle|V\rangle + |V\rangle|H\rangle)/\sqrt{2}$, and $(|H\rangle|V\rangle - |V\rangle|H\rangle)/\sqrt{2}$, (in experiment by J.-W. Pan [6], the four states are: $(|H\rangle|V\rangle + |V\rangle|H\rangle)/\sqrt{2}$, $(|H\rangle|V\rangle - |V\rangle|H\rangle)/\sqrt{2}$, $(|H\rangle|V\rangle + i|V\rangle|H\rangle)/\sqrt{2}$ and $(|H\rangle|V\rangle - i|V\rangle|H\rangle)/\sqrt{2}$), where $H(V)$ means the horizontal (vertical) polarization mode of photons. The two photons are distinguishable by a fixed time delay Δt_p , which is known to Alice and Bob. Then Alice applies a time delay operation to the V photons and before Bob detects the two photons, he applies a same time delay operation to the H photons. Finally, Bob detects the two photons in the $|H\rangle|V\rangle$, $|V\rangle|H\rangle$ basis

or $\frac{1}{\sqrt{2}}(|H\rangle|V\rangle + |V\rangle|H\rangle)$, $\frac{1}{\sqrt{2}}(|H\rangle|V\rangle - |V\rangle|H\rangle)$ basis. Due to the fact that $|\psi^-\rangle = \frac{1}{\sqrt{2}}(|H\rangle|V\rangle - |V\rangle|H\rangle)$ is invariant under collective unitary transformation, this scheme is insensitive to phase fluctuations from Alice's and Bob's interferometers. If the interval of the time between the two photons is just Δt_p , Bob will successfully get Alice's qubit and this probability will be $2/3$ assuming the collective noise is totally random. Besides this, photons from the same pair can provide precise time references for each other. So in this scheme, accurate synchronization clock is unnecessary.

BB84-type QKD protocols which are the most-widely used QKD protocol, needs single photon source which is not practical for present technology. Usually, real-file QKD setups [7, 8, 9, 10, 11] use attenuated laser pulses (weak coherent states) instead. It means the laser source is equivalent to a one that emits n -photon state $|n\rangle$ with probability $P_n = \frac{\mu^n}{n!} e^{-\mu}$, where μ is average photon number of the attenuated laser pulses. This photon number Poisson distribution stems from the coherent state $|\sqrt{\mu}e^{i\theta}\rangle$ of laser pulse. Therefore, a few multi-photon events in the laser pulses emitted from Alice open the door of Photon-Number-Splitting attack (PNS attack) [12, 13, 14] which makes the whole QKD process insecure. Fortunately, decoy states QKD theory [15, 16, 17, 18, 26], as a good solution to beat PNS attack, has been proposed. And some prototypes of decoy state QKD have been implemented [19, 20, 21, 22, 23, 24, 25]. The key point of decoy states QKD is to calculate the lower bound of counting rate of single-photon pulses (S_1^L) and upper bound of quantum bit error rate (QBER) of bits generated by single-photon pulses (e_1^U). Many methods to improve performance of decoy states QKD have been presented, including more decoy states [26], nonorthogonal decoy-state method [27], photon-number-resolving method [28], herald single photon source method [29, 30], modified coherent state source method [31]. And for the intensity fluctuations of the laser pulses, Ref. [34] and [35] give good solutions.

As a BB84-type protocol, Boileau's scheme is still vulnerable to PNS attack. This problem will be discussed in details in the section II, in which we propose a novel type of PNS attack. In the Section III, we propose a decoy states method

to overcome this problem. In Section IV, a numerical simulation will be given. Finally, we will give a summary to end this paper.

II. PNS ATTACK IN BOILEAU'S SCHEME

To implement Boileau's scheme, an ideal two-photon states source which is far from present technology, is needed. In practice, two-photon states are generated by parametric down-conversion source (PDCS), which will emit n -photon ($n > 1$) pairs with certain probability. However, the state from a type-II PDCS can be written like [32]:

$$|\psi\rangle = (\cosh\chi)^{-2} \sum_{n=0}^{\infty} \sqrt{n+1} e^{in\theta} \tanh^n \chi |\Phi_n\rangle, \quad (1)$$

in which, $|\Phi_n\rangle$ is the state of n -photon pair, given by:

$$|\Phi_n\rangle = \frac{1}{\sqrt{n+1}} \sum_{m=0}^n (-1)^m |n-m, m\rangle_a |m, n-m\rangle_b \quad (2)$$

Here, $|n, m\rangle_{a(b)} = |H\rangle_{a(b)}^{\otimes n} |V\rangle_{a(b)}^{\otimes m}$, a, b means the two spatial output modes of PDCS respectively. By randomizing the phase θ [15], we can write the density matrix of the PDCS as $\rho_\lambda = \int (d\theta/(2\pi)) |\psi\rangle\langle\psi| = P_n(\lambda) |\Phi_n\rangle\langle\Phi_n|$, where, $P_n(\lambda) = (n+1)\lambda^n/(1+\lambda)^{n+2}$, $\lambda = \sinh^2\chi$, which is half of the average number of photon pairs generated by one pumping pulse and could be adjusted by the intensity of the pumping pulsed. Therefore, PDCS is really just a photon-number states source emitting n -photon pairs $|\Phi_n\rangle$ with probability $P_n(\lambda)$. For implementations that do not apply phase randomization, Eve may attack this QKD system more powerfully [36]. Therefore, for simplicity we assume that Alice have applied phase randomization to her photon pairs.

Here we focus on the attack to 2-photon pairs, because the 2-photon pairs are dominant among the multi-photon pairs. For the practical implementation [6] by Pan, Alice delays b mode of the two spatial outputs of PDCS with Δt_p . Then through phase-modulation by Pockel cells [6] 2-photon pairs states could be described in creation operators form like this:

$$\begin{aligned} |-\rangle &= \frac{1}{2\sqrt{3}} (H_a^{+2} V_b^{+2} - 2H_a^+ V_a^+ H_b^+ V_b^+ + V_a^{+2} H_b^{+2}) |\text{vacuum}\rangle \\ |+\rangle &= \frac{1}{2\sqrt{3}} (H_a^{+2} V_b^{+2} + 2H_a^+ V_a^+ H_b^+ V_b^+ + V_a^{+2} H_b^{+2}) |\text{vacuum}\rangle \\ |0\rangle &= \frac{1}{2\sqrt{3}} (H_a^{+2} V_b^{+2} + 2iH_a^+ V_a^+ H_b^+ V_b^+ - V_a^{+2} H_b^{+2}) |\text{vacuum}\rangle \\ |1\rangle &= \frac{1}{2\sqrt{3}} (H_a^{+2} V_b^{+2} - 2iH_a^+ V_a^+ H_b^+ V_b^+ - V_a^{+2} H_b^{+2}) |\text{vacuum}\rangle \end{aligned} \quad (3)$$

where, H_a^+ , H_b^+ , V_a^+ , and V_b^+ represent the creation operators for horizontal polarized photons in a mode, horizontal polarized photons in b mode, vertical polarized photons in a mode and vertical polarized photons in b mode. For simplicity, we assume Eve add a beam splitter (BS) to the both modes a and b and we name the two spatial mode of the output of the BS is

1 and 2. Now Eve has 4 spatial-temporal modes $a1, a2, b1$ and $b2$, and creator operators for horizontal-polarized and vertical-polarized photons in these new modes are correlated to modes a and b by $H_a^+ = (1/\sqrt{2})(H_{a1}^+ - H_{a2}^+)$, $V_a^+ = (1/\sqrt{2})(V_{a1}^+ - V_{a2}^+)$, $H_b^+ = (1/\sqrt{2})(H_{b1}^+ - H_{b2}^+)$, and $V_b^+ = (1/\sqrt{2})(V_{b1}^+ - V_{b2}^+)$. Then Eve can post-select the states that each of modes $a1, b1, a2$ and $b2$ has one and only one photon respectively. We should notice that: although through just one BS the probability of success of this post-selection is just 1/4, Eve may use many BSs to make sure that this probability will be close to 1. And states $|-\rangle$, $|+\rangle$, $|0\rangle$ and $|1\rangle$ will be transformed to:

$$\begin{aligned} |-\rangle' &= \frac{1}{2\sqrt{2}} ((H_{a1} V_{b1} - V_{a1} H_{b1})(H_{a2} V_{b2} - V_{a2} H_{b2}) \\ &\quad + (H_{a1} V_{b2} - V_{a1} H_{b2})(H_{a2} V_{b1} - V_{a2} H_{b1})) \\ |+\rangle' &= \frac{1}{2\sqrt{2}} ((H_{a1} V_{b1} + V_{a1} H_{b1})(H_{a2} V_{b2} + V_{a2} H_{b2}) \\ &\quad + (H_{a1} V_{b2} + V_{a1} H_{b2})(H_{a2} V_{b1} + V_{a2} H_{b1})) \\ |0\rangle' &= \frac{1}{2\sqrt{2}} ((H_{a1} V_{b1} + iV_{a1} H_{b1})(H_{a2} V_{b2} + iV_{a2} H_{b2}) \\ &\quad + (H_{a1} V_{b2} + iV_{a1} H_{b2})(H_{a2} V_{b1} + iV_{a2} H_{b1})) \\ |1\rangle' &= \frac{1}{2\sqrt{2}} ((H_{a1} V_{b1} - iV_{a1} H_{b1})(H_{a2} V_{b2} - iV_{a2} H_{b2}) \\ &\quad + (H_{a1} V_{b2} - iV_{a1} H_{b2})(H_{a2} V_{b1} - iV_{a2} H_{b1})) \end{aligned} \quad (4)$$

where $H(V)_x$ represents state vector $|H(V)\rangle_x$ for abbreviation and the same below. Then Eve could use a unitary transformation $\mathcal{U}_1$ to the photons in modes $a1$ and $b2$. The definition of $\mathcal{U}_1$ is given by $\mathcal{U}_1 H V E_0 = H V E_1$, $\mathcal{U}_1 V H E_0 = V H E_1$, $\mathcal{U}_1 H H E_0 = H H E_2$ and $\mathcal{U}_1 V V E_0 = V V E_2$, in which E_x is an assist state of Eve and satisfying $\langle E_0 | E_1 \rangle = \langle E_0 | E_2 \rangle = \langle E_1 | E_2 \rangle = 0$. Eve post-select E_1 through projection $P_1 = |E_1\rangle\langle E_1|$ and then the four states will be mapped into the below states with probability 75%.

$$\begin{aligned} |-\rangle'' &= \frac{1}{\sqrt{5}} (2|X\rangle - |Y\rangle) \\ |+\rangle'' &= \frac{1}{\sqrt{5}} (2|X\rangle + |Y\rangle) \\ |0\rangle'' &= \frac{1}{\sqrt{5}} (2|X'\rangle + i|Y\rangle) \\ |1\rangle'' &= \frac{1}{\sqrt{5}} (2|X'\rangle + i|Y\rangle) \end{aligned} \quad (5)$$

where, $|X\rangle = (1/\sqrt{2})(H_{a1} V_{b1} H_{a2} V_{b2} + V_{a1} H_{b1} V_{a2} H_{b2})$, $|Y\rangle = (1/\sqrt{2})(H_{a1} H_{b1} V_{a2} V_{b2} + V_{a1} V_{b1} H_{a2} H_{b2})$ and $|X'\rangle = (1/\sqrt{2})(H_{a1} V_{b1} H_{a2} V_{b2} - V_{a1} H_{b1} V_{a2} H_{b2})$. Now, Eve can construct another unitary transformation $\mathcal{U}_2$ defined by: $\mathcal{U}_2 |X\rangle |E_0\rangle = (\sqrt{3}|Z\rangle |E_1\rangle + |X\rangle |E_2\rangle)/2$, $\mathcal{U}_2 |X'\rangle |E_0\rangle = (\sqrt{3}|Z\rangle |E_3\rangle + |X'\rangle |E_2\rangle)/2$ and $\mathcal{U}_2 |Y\rangle |E_0\rangle = |Y\rangle |E_2\rangle$. Here, $|E\rangle$ represents an assist states of Eve and $\langle E_0 | E_1 \rangle = \langle E_0 | E_2 \rangle = \langle E_1 | E_2 \rangle = 0$. And $|Z\rangle$ is any states of photon in modes $a1, b1, a2$ and $b2$. With $\mathcal{U}_2$ and projection operation $P_2 = |E_2\rangle\langle E_2|$,

the four photon states will be mapped to the followed form with probability 40%.

$$\begin{aligned}
|-\rangle''' &= \frac{1}{\sqrt{2}}(|X\rangle - |Y\rangle) \\
&= \frac{1}{\sqrt{2}}(H_{a1}V_{b2} - V_{a1}H_{b2})\frac{1}{\sqrt{2}}(H_{a2}V_{b1} - V_{a2}H_{b1}) \\
|+\rangle''' &= \frac{1}{\sqrt{2}}(|X\rangle + |Y\rangle) \\
&= \frac{1}{\sqrt{2}}(H_{a1}V_{b2} + V_{a1}H_{b2})\frac{1}{\sqrt{2}}(H_{a2}V_{b1} + V_{a2}H_{b1}) \\
|0\rangle''' &= \frac{1}{\sqrt{2}}(|X\rangle + i|Y\rangle) \\
&= \frac{1}{\sqrt{2}}(H_{a1}V_{b2} + iV_{a1}H_{b2})\frac{1}{\sqrt{2}}(H_{a2}V_{b1} + iV_{a2}H_{b1}) \\
|1\rangle''' &= \frac{1}{\sqrt{2}}(|X\rangle - i|Y\rangle) \\
&= \frac{1}{\sqrt{2}}(H_{a1}V_{b2} - iV_{a1}H_{b2})\frac{1}{\sqrt{2}}(H_{a2}V_{b1} - iV_{a2}H_{b1})
\end{aligned} \tag{6}$$

Obviously, with the states $|-\rangle'''$, $|+\rangle'''$, $|0\rangle'''$ and $|1\rangle'''$, Eve can keep one pair and send the other pair to Bob through a special channel controlled by herself. When Alice and Bob do basis reconciliation, Eve will get all secret information. This is just the same as PNS attack [12, 13, 14].

Let us review our attack strategy. First, Eve divides the two photons in modes a and b into modes $a1$, $a2$ and $b1$, $b2$ respectively. With many BSs, success probability of this step is close to 1. Second, Eve applies unitary transformation $\mathcal{U}_1$ and projection P_1 , she gets an intermediate state with success probability 75%. Finally, She applies unitary transformation $\mathcal{U}_2$ and projection P_2 , she gets the final state which she can launch PNS attack immediately and success probability of this step is 40%. Overall, for 2-photon pairs Eve will launch PNS attack with probability of $75\% \times 40\% = 30\%$ or discard a failure case with probability $1 - 30\% = 70\%$.

According to the above fact and the discussion of Ref. [12, 13, 14], we know the security distance (L) of this scheme must obey $P_1(\lambda)(10^{-kL/10})^2 \geq P_2(\lambda) \times 30\%$ in which k is the transmission fiber loss constance. If we assume $k = 0.2\text{dB/km}$ which is a typical value of this constance and $\lambda = 0.1$, we obtain $L \leq 37.4\text{km}$. This is a highly unsatisfactory situation. How to prolong the security distance is what we will discuss in the next section.

III. DECOY STATES TO BOILEAU'S SCHEME

The rate of secret key bits (R) for BB84 protocol with non-ideal source can be determined by GLLP [33]:

$$R \geq R^L = q[-Q_\lambda f(E_\lambda)H_2(E_\lambda) + P_1(\lambda)S_1^L(1 - H_2(e_1^U))] \tag{7}$$

Here, R^L represents the lower bound of R , q depends on protocol (1/2 for Boileau's scheme), Q_λ is the overall counting

rate for the photon pairs, λ is half of the average number of the photon pairs, $f(E_\lambda)$ is error correction efficiency, E_λ is the quantum bit error rate (QBER) of the key bit, H_2 is the binary Shannon information function, S_1 is the counting rate for the 1-photon pairs, and e_1 is the QBER of the key bits generated by the 1-photon pairs. Similar to BB84 based on weak coherent states, we need to modulate λ to several values randomly. Through watching counting rates for different λ , we can obtain the lower bound of S_1 (S_1^L) and the upper bound of e_1 (e_1^U). Finally, R^L can be obtained by equation (7).

Our 3-intensity protocol is: Alice randomly emits photon pairs of density matrix ρ_λ , $\rho_{\lambda'}$, and 0 (λ for signal states, λ' ($\lambda > \lambda'$) and 0 for decoy states), then Bob can get their counting rates Q_λ , $Q_{\lambda'}$ and S_0 . With formulas we derived later, S_1^L and e_1^U can be obtained. Finally, R^L is given by equation (7). Now we drive these formulas.

The counting rates for the two intensity (λ and λ') photon pairs is determined by:

$$Q_\lambda = \sum_{n=0}^{\infty} P_n(\lambda)S_n \tag{8}$$

$$Q_{\lambda'} = \sum_{n=0}^{\infty} P_n(\lambda')S_n \tag{9}$$

where, S_n represents the counting rate for n -photon pair states $|\Phi_n\rangle$. Then QBER for the λ (E_λ) is determined by:

$$E_\lambda Q_\lambda = \sum_{n=0}^{\infty} e_n P_n(\lambda)S_n \tag{10}$$

In which, e_n is the QBER of the key bits generated by the n -photon pairs $|\Phi_n\rangle$. Before the derivation of the formula to calculate S_1^L and e_1^U , we prove that $\frac{P_2(\lambda)}{P_2(\lambda')}P_n(\lambda') \leq P_n(\lambda)$ for all of $n \geq 2$.

$$\begin{aligned}
&\frac{P_2(\lambda)}{P_n(\lambda)} - \frac{P_2(\lambda')}{P_n(\lambda')} \\
&= \frac{3}{n+1}((1 + \frac{1}{\lambda})^{n-2} - (1 + \frac{1}{\lambda'})^{n-2}) \leq 0
\end{aligned} \tag{11}$$

With this result, we can deduce the formula for calculating S_1^L :

$$\begin{aligned}
Q_\lambda &= P_0(\lambda)S_0 + P_1(\lambda)S_1 + P_2(\lambda)S_2 + P_3(\lambda)S_3 + \dots \\
&\geq P_0(\lambda)S_0 + P_1(\lambda)S_1 + \frac{P_2(\lambda)}{P_2(\lambda')} \sum_{n=2}^{\infty} P_n(\lambda')S_n
\end{aligned} \tag{12}$$

With equation (9), we have:

$$S_1^L = \frac{(P_2(\lambda')P_0(\lambda) - P_2(\lambda)P_0(\lambda'))S_0 + P_2(\lambda)Q_{\lambda'} - P_2(\lambda')Q_\lambda}{P_2(\lambda)P_1(\lambda') - P_2(\lambda')P_1(\lambda)} \tag{13}$$

According to equation (10) and [18], e_1^U can be given by:

$$e_1^U = \frac{(E_\lambda Q_\lambda - \frac{S_0 P_0(\lambda)}{2})}{P_1(\lambda)S_1^L} \tag{14}$$

With equation (13) and (14), S_1^L and e_1^U can be obtained. Finally, R^L is given by equation (7).

For experiment, 2-intensity decoy states protocol is quite convenient [25]. In this case, Alice randomly emits photon pairs of density matrix ρ_λ for signal states, $\rho_{\lambda'}$ for decoy states, then Bob can get their counting rates Q_λ , $Q_{\lambda'}$. We now deduce the formula to calculate S_1^L and e_1^U just from Q_λ , $Q_{\lambda'}$.

According to equation (10), the upper bound of S_0 (S_0^U) can be given by:

$$S_0^U = \frac{2E_\lambda Q_\lambda}{P_0(\lambda)} \quad (15)$$

Then from equation (10), S_1^L for two-intensity case can be given by:

$$S_1^L = \frac{2(P_2(\lambda')P_0(\lambda) - P_2(\lambda)P_0(\lambda')) \frac{E_\lambda Q_\lambda}{P_0(\lambda)} + P_2(\lambda)Q_{\lambda'} - P_2(\lambda')Q_\lambda}{(P_2(\lambda)P_1(\lambda') - P_2(\lambda')P_1(\lambda))P_0(\lambda)} \quad (16)$$

To get e_1^U for two intensity case, we just set lower bound of S_0 (S_0^L) to be 0, then with equation (10) and (16), e_1^U is given by:

$$e_1^U = \frac{E_\lambda Q_\lambda}{P_1(\lambda)S_1^L} \quad (17)$$

Equations (16) and (17) are for 2-intensity case. With these equations, we have established the basic methods to beat PNS attack in Boileau's QKD scheme. Next, we will make sure that this decoy states method can improve the performance of Boileau's QKD scheme impressively.

IV. IMPROVEMENT BY DECOY STATES

Now, we will show the improvement for the performance by the introduction of decoy states through the numerical simulations. In the followed discussions and simulations, we neglect the error induced by channel and assume Bob's measurements are perfect except a few dark counts for simplicity. According to Ref. [6], Bob's measurement is equivalent to the projection to the polarization states F and S defined by $H = (F + S)/\sqrt{2}$ and $V = (F - S)/\sqrt{2}$ respectively. We rewrite the encoding states $|+\rangle$ and $|-\rangle$ in the form of F and S : $|+\rangle = \frac{1}{\sqrt{n+1}} \sum_{m=0}^n (-1)^m F_a^{n-m} S_a^m F_b^{n-m} S_b^m$, $|-\rangle = \frac{1}{\sqrt{n+1}} \sum_{m=0}^n (-1)^m F_a^{n-m} S_a^m F_b^m S_b^{n-m}$. For Bob, if he observes the $F_a S_b$ or $S_a F_b$, it's will be $|+\rangle$ while the $F_a F_b$ or $S_a S_b$ is for the result of $|-\rangle$. According to Ref.[18], the transmission efficiency for the n -photon pulses η_n can be written as $\eta_n = 1 - (1 - \eta)^n$, in which η is the transmission efficiency of the fiber channel and $\eta = 10^{(-kL/10)}$, K is the transmission fiber loss constance and L is the fiber length. Since our goal is to show the difference between the original Boileau's scheme and this scheme with decoy states but not the exact R^L verse fiber length, we take the efficiency of the detector and loss due to projection to the DFS space or other causes just as a part of

fiber loss and don't care these values. We assume the dark counting rates of the detectors is D . Since Bob must neglect all the three or four folds counts, S_n can be written as:

$$S_n = \frac{(1-D)^2}{n+1} \sum_{m=0}^n ((\eta_{n-m}(1-\eta)^m + \eta_m(1-\eta)^{n-m})^2 + 4\eta_{n-m}(1-\eta)^m(1-\eta)^n D + 4\eta_m(1-\eta)^{n-m}(1-\eta)^n D + 4(1-\eta)^{2n} D^2) \quad (18)$$

Then with equation (8), we can get the formulas to estimate the Q_λ and $Q_{\lambda'}$.

$$Q_\lambda = \sum_{n=0}^{\infty} P_n(\lambda) S_n = \frac{2(1-D)^2}{(1 + \lambda\eta(3-\eta) + \lambda^2\eta^2(2-\eta))^2} \times (4\lambda\eta D(1-\eta)(1+\lambda\eta) + 2D^2(1+\lambda\eta)^2 + \lambda\eta^2(1 + \lambda^2(2-\eta)\eta + \lambda(\eta^2 - 2\eta + 3))) \quad (19)$$

For simplicity we neglect the probability that a survived photon hitting a wrong detector, then e_n is written like:

$$e_n S_n = \left[\sum_{m=0}^n (2\eta_{n-m}(1-\eta)^m(1-\eta)^{n-m}\eta_m + 2\eta_m(1-\eta)^{n-m}(1-\eta)^n) + 2\eta_{n-m}(1-\eta)^m(1-\eta)^n D + (1-\eta)^{2n} 2D \right] \frac{(1-D)^2}{n+1} \quad (20)$$

in which, the first term of the summation corresponds to the case of the photons in modes a and b both hitting the detectors. Only when $n \geq 2$, this term does not equal to 0. The second and third terms in above summation represent to the case photons in only one mode (a or b) hit the detector. The dark count of one detector may result in QBER in this situation. The last term of the summation is for the case of all the photons are absorbed by fiber.

With this, we can estimate the QBER E_λ as:

$$E_\lambda = \sum_{n=0}^{\infty} P_n(\lambda) e_n S_n / Q_\lambda = (D + \lambda D \eta + \lambda \eta (1-\eta))^2 \times [4\lambda D \eta (1-\eta)(1+\lambda\eta) + 2D^2(1+\lambda\eta)^2 + \lambda\eta^2(1 + \lambda^2\eta(2-\eta) + \lambda(\eta^2 - 2\eta + 3))]^{-1} \quad (21)$$

Now with equations (19) and (21) and setting $k = 0.2 \text{ dB/km}$, $D = 10^{-6} / \text{pulse}$, and $f(E_\lambda) = 1.2$, the Q_λ , $Q_{\lambda'}$, E_λ can be calculated by numerical simulations. Then with equations (13) and (14), the S_1^L and e_1^U can be obtained. Finally, the relation between R^L and fiber length L can be get. And the results are depicted in Fig. 1. In Fig. 1, the solid curve is for the case that no decoy states is employed. In this case, for the calculation of S_1^L and e_1^U we have to assume that $S_n = 1(n \geq 2)$ and with

equation (15), then obviously the S_1 is given by:

$$S_1^L = \frac{Q_\lambda - P_0(\lambda)S_0^U - \sum_{n=2}^{\infty} P_2(\lambda)}{P_1(\lambda)} \quad (22)$$

$$= \frac{Q_\lambda(1 - 2E_\lambda) - (1 - P_0(\lambda) - P_1(\lambda))}{P_1(\lambda)}$$

The e_1^U is then calculated by equation (14). With this method,




FIG. 1: Lower bound of secret bit generation rate (R_1^L) verse fiber length L . Solid curve: no decoy states is employed, Alice just emits PDCS with half average number of photon pair $\lambda = 0.1$. Dashed curve: for the 3-intensity case, Alice randomly used PDCS with half average number of photon pair $\lambda = 0.1$, $\lambda' = 0.01$ and 0.

R^L is obtained by equation (7). From Fig. 1, we found that the 3-intensity decoy states method can improve the performance of Boileau's scheme dramatically. The longest security distance in original Boileau's scheme is about 18 km while this distance for 3-intensity decoy states method will be 40 km. This improvement means about the 4.4dB increase in longest security distance.

V. CONCLUSION

According to above discussions, we proved that through the introduction of decoy states method, especially the 3-intensity decoy states, the performance of Boileau's DFS type QKD would be dramatically improved. Thanks to 3-intensity decoy state protocol the increase of longest security distance can be 4.4dB. This increase relies on the ability of 3-intensity decoy states protocol can obtain a tighter bound of S_1^L and e_1^U . Furthermore one can estimate the information leaked to Eve with high precision and higher key bit rate and longer security distance can be obtained. We hope that our protocol could be implemented soon.

This work was supported by National Fundamental Research Program of China (2006CB921900), National Natural Science Foundation of China (60537020, 60621064) and the Innovation Funds of Chinese Academy of Sciences. To whom correspondence should be addressed, Email: zwzhou@ustc.edu.cn and zfhfan@ustc.edu.cn.

-
- [1] C. H. Bennett, G. Brassard, *Proceedings of IEEE International Conference on Computers, Systems, and Signal Processing*, (IEEE, 1984), pp. 175-179.
 - [2] A. K. Ekert, *Phys. Rev. Lett.* **67**, 661 (1991)
 - [3] N. Gisin et al., *Rev. Mod. Phys.* **74**, 145 (2002)
 - [4] Z. D. Walton, A. F. Abouraddy, A. V. Sergienko, B. E. A. Saleh, and M. C. Teich, *Phys. Rev. Lett.* **91**, 087901 (2003)
 - [5] J.-C. Boileau, R. Laflamme, M. Laforest, and C. R. Myers, *Phys. Rev. Lett.* **93**, 220501 (2004)
 - [6] Teng-Yun Chen, Jun Zhang, J.-C. Boileau, Xian-Min Jin, Bin Yang, Qiang Zhang, Tao Yang, R. Laflamme, and Jian-Wei Pan, *Phys. Rev. Lett.* **96**, 150504 (2006)
 - [7] M. Bourennane et al., *Opt. Express* **4**, 383 (1999)
 - [8] D. Stucki et al., *New. J. Physics*, **4**, 41, (2002)
 - [9] H. Kosaka et al., *Electron. Lett.* **39**, 1199 (2003)
 - [10] C. Gobby, Z. L. Yuan, and A. J. Shields, *Appl. Phys. Lett.* **84**, 3762 (2004);
 - [11] X.-F. Mo et al., *Optics Letters*, Vol. **30**, Issue 19, pp. 2632-2634 (October 2005)
 - [12] B. Huttner, N. Imoto, N. Gisin, and T. Mor, *Phys. Rev. A* **51**, 1863 (1995);
 - [13] G. Brassard et al., *Phys. Rev. Lett.* **85**, 1330 (2000).
 - [14] N. Lutkenhaus, *Phys. Rev. A* **61**, 052304 (2000).
 - [15] W.-Y. Hwang, *Phys. Rev. Lett.* **91**, 057901 (2003).
 - [16] H.-K. Lo, X. Ma, and K. Chen, *Phys. Rev. Lett.* **94**, 230504 (2005).
 - [17] X.-B. Wang, *Phys. Rev. Lett.* **94**, 230503 (2005);
 - [18] X. Ma et al., *Phys. Rev. A* **72**, 012326 (2005).
 - [19] Y. Zhao et al., *Phys. Rev. Lett.* **96**, 070502 (2006)
 - [20] Yi Zhao et al, *Proceedings of IEEE International Symposium on Information Theory 2006*, pp. 2094-2098
 - [21] C.-Z. Peng et al., *Phys. Rev. Lett.* **98**, 010505 (2007)
 - [22] D. Rosenberg, J. W. Harrington, P. R. Rice, et al., *Phys. Rev. Lett.* **98**, 010503 (2007)
 - [23] Z. L. Yuan, A. W. Sharpe, and A. J. Shields, *Appl. Phys. Lett.* **90** 011118 (2007)
 - [24] Tobias Schmitt-Manderbach et al., *Phys. Rev. Lett.* **98**, 010504 (2007)
 - [25] Z.-Q. Yin et al., *quant-ph/0704.2941* (2007)
 - [26] X.-B. Wang, *Phys. Rev. A* **72**, 012322 (2005)
 - [27] J.-B. Li, and X.-M. Fang, *Chin. Phys. Lett.* **23**, No. 4 (2006)
 - [28] Qing-yu Cai, and Yong-gang Tan, *Phys. Rev. A* **73**, 032305 (2006)
 - [29] Tomoyuki Horikiri, and Takayoshi Kobayashi, *Phys. Rev. A* **73**, 032331 (2006)
 - [30] Qin Wang, X.-B. Wang, and G.-C. Guo, *Phys. Rev. A* **75**, 012312 (2007)
 - [31] Z.-Q. Yin, Z.-F. Han, F.-W. Sun, and G.-C. Guo, *Phys. Rev. A* **76**, 014304 (2007)
 - [32] Xiongfeng Ma, Chi-Hang Fred Fung, and Hoi-Kwong Lo, *Phys. Rev. A* **76**, 012307 (2007)
 - [33] D. Gottesman, H.-K. Lo, N. Lütkenhaus, and J. Preskill, *Quantum Inf. Comput.* **4**, 325 (2004).
 - [34] X.-B. Wang, C.-Z. Peng, and J.-W. Pan, *Appl. Phys. Lett.* **90**,

031110 (2007)

(2005)

[35] X.-B. Wang, Phys. Rev. A **75**, 052301 (2007)

[36] Hoi-Kwong Lo and John Preskill, arXiv:quant-ph/0504209